

On Strong Controllability of Infinite-Dimensional Linear Systems

A. R. SOUROUR

*Department of Mathematics, University of Victoria,
Victoria, British Columbia V8W 2Y2, Canada*

Submitted by J. P. LaSalle

If an infinite-dimensional linear system is strongly controllable (i.e., every state can be reached from any state in finite time), then it is strongly controllable in uniform finite time.

Consider the infinite-dimensional linear systems

$$x_n = Ax_{n-1} + Bu_{n-1} \quad (1)$$

and

$$dx/dt = Ax(t) + Bu(t), \quad x(0) = x_0, \quad (2)$$

with Banach spaces \mathcal{X} and \mathcal{U} as the state space and the control space, respectively. Either system is called *strongly controllable* if any state x in \mathcal{X} can be reached from any initial state x_0 in finite time (which may depend on x and x_0). If the system is strongly controllable we prove that it is strongly controllable in uniform finite time, i.e., there is an integer n (in the discrete case) or time t (in the continuous case) such that every state x can be reached from any state x_0 in n steps (or in time t). A proof given by Fuhrmann [4] is not valid unless \mathcal{X} and \mathcal{U} are Hilbert spaces. The proof in [4] is based on an operator theory theorem of Douglas [2] which is not always true if the spaces involved are not assumed to be Hilbert spaces. (In Banach spaces a counterexample due to Douglas is given in Embry [3].)

We start with two lemmas on operators. The notation is standard; the set of all bounded linear operators from a Banach space \mathcal{X} to a Banach space \mathcal{Y} is denoted by $\mathcal{B}(\mathcal{X}, \mathcal{Y})$.

LEMMA 1. *Let $\mathcal{X}_n, \mathcal{Y}_n$ ($n = 1, 2, \dots$) be Banach spaces and let $T_n \in \mathcal{B}(\mathcal{Y}_n, \mathcal{X})$. If $\mathcal{X} = \bigcup_n T_n \mathcal{Y}_n$, then $\mathcal{X} = T_m \mathcal{Y}_m$ for some m .*

Proof. Let $\mathcal{S}_n = \{y \in \mathcal{Y}_n : \|y\| < 1\}$ be the open unit ball in \mathcal{Y}_n . We have

$\mathcal{X} = \bigcup_n \bigcup_k A_n(k\mathcal{Y}_n)$. By the Baire category theorem, there are positive integers n and k such that $\overline{T_n(k\mathcal{Y}_n)}$ contains an open set $\{x \in \mathcal{X} : \|x - x_0\| < r\}$ for some $x_0 \in \mathcal{X}$ and $r > 0$. (The bar indicates closure in the norm topology.) Thus $\overline{T_n(2k\mathcal{Y}_n)}$ contains the ball $\mathcal{X}_r = \{x \in \mathcal{X} : \|x\| < r\}$. The proof of the open mapping theorem [1, p. 56] shows that $\mathcal{X}_r \subseteq T_n(4k\mathcal{Y}_n)$ and so $\mathcal{X} = T_n\mathcal{Y}_n$. ■

LEMMA 2. *Let \mathcal{X} , \mathcal{Y}_n ($n=1, 2, \dots$) be Banach spaces and let $T_n \in \mathcal{B}(\mathcal{Y}_n, \mathcal{X})$. If \mathcal{X} is the linear span of the operator ranges $T_n\mathcal{Y}_n$, then \mathcal{X} is the linear span of finitely many ranges $\{T_n\mathcal{Y}_n : n=1, 2, \dots, m\}$ for some m .*

Proof. For every n , let $\mathcal{X}_n = \mathcal{Y}_1 \oplus \dots \oplus \mathcal{Y}_n$ with norm given by $\|(y_1, \dots, y_n)\| = \sum_{j=1}^n \|y_j\|$. Let $R_n: \mathcal{X}_n \rightarrow \mathcal{X}$ be the bounded operator defined by $R_n(y_1, \dots, y_n) = \sum_{j=1}^n T_j y_j$. The assumption that \mathcal{X} is the linear span of $T_n\mathcal{Y}_n$ means that $\mathcal{X} = \bigcup_n R_n\mathcal{X}_n$. Applying Lemma 1 to R_n establishes the result. (The idea of using direct sums is suggested by a proof of a theorem in Banach algebras due to A. M. Davie (unpublished) shown to me by Peter Rosenthal.) ■

Let us now consider the discrete system (1), where $A \in \mathcal{B}(\mathcal{X})$ and $B \in \mathcal{B}(\mathcal{Y}, \mathcal{X})$. The solution is given by $x_n = A^n x_0 + \sum_{j=0}^{n-1} A^{n-1-j} B u_j$.

THEOREM 1. *If system (1) is strongly controllable, then it is strongly controllable in uniform finite time.*

Proof. The System (1) is strongly controllable if and only if for every x in \mathcal{X} , there is a positive integer n and vectors u_0, \dots, u_n in \mathcal{Y} such that $x = \sum_{j=0}^{n-1} A^j B u_j$. This simply means that \mathcal{X} is the linear span of the ranges of $A^j B$ ($j=0, 1, \dots$). By Lemma 2, \mathcal{X} must be the linear span of $A^j B$ ($j=0, 1, \dots, n$) for some n . This is the desired conclusion. ■

Next we look at the continuous system

$$dx/dt = Ax(t) + Bu(t), \quad x(0) = x_0, \quad (2)$$

where \mathcal{X} and \mathcal{Y} are Banach spaces, $B \in \mathcal{B}(\mathcal{Y}, \mathcal{X})$, A is the infinitesimal generator of a strongly continuous semigroup of operators $\{T(t) : t \geq 0\}$ on \mathcal{X} , and u belongs to a function space \mathcal{F} consisting of measurable \mathcal{Y} -valued functions on $[0, \infty)$ and satisfying some technical conditions [4]. Instead of listing these conditions we will simply assume that \mathcal{F} is the space of all locally L^1 functions from $[0, \infty)$ into \mathcal{Y} . This guarantees the existence of the integrals $\int_0^t T(t-s) Bu(s) ds$. Furthermore

$$\left\| \int_0^t T(t-s) Bu(s) ds \right\| \leq \sup_{0 \leq t \leq t} \|T_t\| \|B\| \int_0^t \|u(s)\| ds.$$

With the appropriate interpretation (see [4]), the solution to (2) is

$$x(t) = T(t)x_0 + \int_0^t T(t-s)Bu(s)ds.$$

THEOREM 2. *If system (2) is strongly controllable, then it is controllable in uniform finite time.*

Proof. For every $t > 0$, let S_t be the bounded operator from $L^1([0, t], \mathcal{Z})$ into \mathcal{X} given by

$$S_t u = \int_0^t T(t-s)Bu(s)ds.$$

Strong controllability is equivalent to the condition that $\mathcal{X} = \bigcup_{t>0} \text{range}(S_t)$. Since $\text{range}(S_t) \subseteq \text{range}(S_n)$ for $t \leq n$, we have $\mathcal{X} = \bigcup_{n=1}^{\infty} \text{range}(S_n)$. By Lemma 1, $\mathcal{X} = \text{range}(S_n)$ for some n and so system (2) is strongly controllable in finite time n . ■

REFERENCES

1. N. DUNFORD AND J. T. SCHWARTZ, "Linear Operators," Part I. Interscience, New York, 1958.
2. R. G. DOUGLAS, On majorization, factorization, and range inclusion of operators on Hilbert space, *Proc. Amer. Math. Soc.* **17** (1966), 413–415.
3. M. R. EMBRY, Factorization of operators on Banach space, *Proc. Amer. Math. Soc.* **38** (1973), 587–590.
4. P. A. FUHRMANN, On weak and strong reachability and controllability of infinite-dimensional linear systems, *J. Optim. Theory Appl.* **9** (1972), 77–89.